

**DECISION**  
**regulating the use of radio frequency channels from the 3600-3800 MHz band**

1. By the Radio Frequency Allocation Plan in Montenegro, the frequency band of 3600-3800 MHz is allocated for fixed wireless access (FWA).
2. The frequency band of 3600-3800 MHz is divided into 28 two-way radio channels with channel spacing of 3.5 MHz and duplex spacing of 100 MHz in compliance with CEPT/ERC/REC T/R 12-08 Recommendation, Annex B. The table below illustrates the way of grouping frequency channels from the 3600-3800 MHz frequency band.

Ordinal number of the channel	Block	Block width [MHz]	Lower band [MHz]	Upper band [MHz]
1-6	A	2x21	3601.0-3622.0	3701.0-3722.0
7	Guard channel	2x3.5	3622.0-3625.5	3722.0-3725.5
8-13	B	2x21	3625.5-3646.5	3725.5-3746.5
14	Guard channel	2x3.5	3646.5-3650.0	3746.5-3750.0
15-20	C	2x21	3650.0-3671.0	3750.0-3771.0
21	Guard channel	2x3.5	3671.0-3674.5	3771.0-3774.5
22-27	D	2x21	3674.5-3695.5	3774.5-3795.5

3. Radio channels with ordinal numbers 1-6, 8-13, 15-20 and 22-27 are grouped in four 2x21 MHz frequency blocks, which is allocated for the implementation of fixed wireless access on national level.
4. Radio channels with ordinal numbers 7, 14, and 21 are guard channels.
5. The manner of use of the frequencies from this band is to be in compliance with CEPT/ECC/REC (04)05 Recommendation.
6. This Decision enters into force on the eight day from the day of its publishing in the Official Gazette of the Republic of Montenegro.

No.:01-1318/1  
Podgorica, 16.04. 2007

**Agency for Telecommunications and Postal Services of Montenegro**

**Zoran Sekulić**  
**Director**

LINK: Radio Frequency Allocation Plan